



A-FIRE

8 zone fire panel with LCD screen

CROSSFIRE 8K LCD

EXITS (FIRE)

Siren outputs with resettable fuse	2
Fault relay	1
Alarm relay	1
Individual outputs by zone	Yes
Error and omission outputs	Yes
Remote outputs with relay	Yes, with the RM8 module

PROGRAMACIÓN

Day / night mode	Yes
Zone mapping for exits	Yes
Cross detection function	Yes
Levels	3 (Useful / Very Useful / Installer)
Test zone / Omission / Evacuation Mode	Yes

ZONAS (INCENDIO)

Maximum number of zones	8
Maximum number of detectors per zone	30

MATERIAL AND DIMENSIONS

Dimensions	321 x 286 x 90 mm
------------	-------------------

GENERAL INFORMATION

Technology	Convencional
Type of Central	Incendio

CERTIFICATION

Normative	EN54-2 / EN54-4
CPR	Yes

DISPLAY

Orientation keys	Yes
Screen	Yes