



**A-SMART-HOME**

**Dimmer conmutable regulable para luz**

**A-WDS86-1L2W**

## SPECIFICATIONS (LIGHT SWITCHES)

|                                     |                              |
|-------------------------------------|------------------------------|
| Backlight                           | <b>Yes</b>                   |
| Electric connection                 | <b>Only with phase cable</b> |
| Adjustment of luminous intensity    | <b>Yes</b>                   |
| Touch panel                         | <b>Yes</b>                   |
| Status recovery after power failure | <b>Yes</b>                   |
| Life cycle                          | <b>100000 ciclos</b>         |

## POWER CONSUMPTION

|                     |                                          |
|---------------------|------------------------------------------|
| Power mode          | <b>AC</b>                                |
| Voltage             | <b>110V ~ 240V</b>                       |
| Standby consumption | <b>0.5W</b>                              |
| Power consumption   | <b>10A</b>                               |
| Potencia de carga   | <b>200W por segmento / 200W en total</b> |

## GENERAL INFORMATION

|      |                                             |
|------|---------------------------------------------|
| Type | <b>Dimmer conmutable regulable para luz</b> |
|------|---------------------------------------------|

## AMBIENT

|                       |                       |
|-----------------------|-----------------------|
| Operating temperature | <b>-20 °C ~ 70 °C</b> |
| Use                   | <b>Indoor</b>         |
| Maximum humidity      | <b>93%</b>            |

## MATERIAL AND DIMENSIONS

|                       |                        |
|-----------------------|------------------------|
| Dimensions            | <b>50 x 50 x 30 mm</b> |
| Net weight            | <b>40 g</b>            |
| Weight with packaging | <b>70 g</b>            |

